



US005863445A

# United States Patent [19]

[11] **Patent Number:** **5,863,445**

**Geisel et al.**

[45] **Date of Patent:** **Jan. 26, 1999**

- [54] **ETCHED COIL UNIBODY DIGITAL DETECTOR**
- [75] Inventors: **Karl E. Geisel**, Montebello, N.Y.;  
**Andrew Biscamp**, Ridgefield Park;  
**Brad Conway**, Harding, both of N.J.
- [73] Assignee: **Control Screening L.L.C.**, Fairfield, N.J.
- [21] Appl. No.: **835,029**
- [22] Filed: **Mar. 27, 1997**
- [51] **Int. Cl.<sup>6</sup>** ..... **B44C 1/22**
- [52] **U.S. Cl.** ..... **216/13; 216/20; 216/33; 324/329; 324/149**
- [58] **Field of Search** ..... **216/13, 16, 20, 216/33, 41; 324/326, 329, 76.39, 76.47, 76.82, 99 D, 149**

5,325,873 7/1994 Hirshi et al. .... 128/899  
 5,569,390 10/1996 Endo ..... 216/13

### FOREIGN PATENT DOCUMENTS

1299183 12/1972 United Kingdom .  
 1315684 5/1973 United Kingdom .

### OTHER PUBLICATIONS

Copies of photographs of C.E.I.A. device (Exhs. 1 through 9).


*Primary Examiner*—William Powell  
*Attorney, Agent, or Firm*—Walter J. Tencza, Jr.

### [57] ABSTRACT

The present invention in one embodiment provides a metal detector comprising a coil, a circuit board on which the coil is etched, a digital signal processor, and a warning circuit, and battery power source. When a sufficient amount of metal is near the coil, the digital signal processor activates a device or devices in the warning circuit. In another embodiment the circuit board on which the coil is placed is used in conjunction with a one piece molded housing. In another embodiment the present invention, provides a metal detector comprising an elongated coil etched onto an elongated circuit board. At least one active device, which is part of detection circuitry is also preferably placed on the elongated circuit board. The detection circuitry in one embodiment, includes circuitry which together with the elongated coil forms an oscillator circuit. The elongated covering case in one embodiment is molded substantially seamlessly by blowmold, extrusion, or injection mold.

- [56] **References Cited**
- U.S. PATENT DOCUMENTS**
- D. 251,363 3/1979 Henault et al. .... D10/47
- D. 251,364 3/1979 Henault et al. .... D10/47
- D. 346,977 5/1994 Fiske ..... D10/47
- 2,502,626 4/1950 Mages ..... 175/183
- 3,444,460 5/1969 Penney, Jr. .... 324/40
- 3,714,563 1/1973 Voll ..... 324/67
- 4,423,377 12/1983 Podhrasky ..... 324/329
- 4,754,469 6/1988 Harding et al. .... 378/88
- 4,775,435 10/1988 Draeger ..... 216/13
- 4,853,617 8/1989 Douglas et al. .... 324/67
- 4,862,316 8/1989 Smith et al. .... 361/220
- 5,055,793 10/1991 Mulcahey ..... 324/326

**19 Claims, 14 Drawing Sheets**






FIG. 1  
(PRIOR ART)

FIG. 2A




FIG. 2B




FIG. 2C




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9





FIG. 10






FIG. 11A




FIG. 11B




FIG. 12B




FIG. 12A




FIG. 12C




FIG. 13




FIG. 14B









FIG. 14D





## ETCHED COIL UNIBODY DIGITAL DETECTOR

### FIELD OF THE INVENTION

This invention relates to the field of metal detectors and more particularly to techniques for providing a coil and detection circuitry and for providing efficient housing for such coil and circuitry.

### BACKGROUND OF THE INVENTION

Penney Jr., U.S. Pat. No. 3,444,460 discloses a conductivity probe **10** which is mounted to measure the conductivity of matter such as fluids. A flat spiral coil **26** etched on a circular circuit board **42** is used as the probing element. (Col. 4, lns. 3-60, FIGS. 1-4). An etched shielding **32** is provided on the opposite side of the circuit board **42**. (Id.) A coaxial conductor **44** surrounds the coil **26**, board **42** and shielding **32**. (Id.) The spiral coil **26** is connected by a conductor **50** to measuring circuitry in probe head assembly **14**. (Col. 5, lns. 8-13, FIGS. 4-5) The conductivity probe **10** shown in Penney Jr., is adapted for mounting within a pipe structure **20**, in which a conducting fluid is located. (Col. 4, lns. 3-18) The coil **26** forms part of a resonant circuit which is driven by a constant current at its resonant frequency. (Col. 5, lns. 13-22) In a vastly different application, Hirschi et al., U.S. Pat. No. 5,325,873, discloses an external probe **10** for detecting resonant circuits **32** and **34** in a feeding tube. (Col. 2, lns. 3-14, col. 4, lns.57-64.) Hirschi et al. specifically discusses a prior art system for detecting a metal object which was not suitable. The external probe **10** includes a circular search head **12** which further comprises a pair of parallel circular circuit boards **15** and **17** each of which contains a coil or coils. (FIGS. 1, 3, and 4) Coil **40**, a circular transmitter coil and two receiver D shaped coils, **42a** and **42b**, are located on circuit board **17**, while second circular transmitter coil **41** and two D shaped coils **44a** and **44b** are located on circuit board **15**. (Id., col. 6, lns. 26-47) The coils are designed to produce a null condition when a target is centered. (See col. 6, lns. 48-55)

In the prior art, metal detector wands were injection molded in at least three sections, generally top, bottom and battery cover. This required higher molding costs, many screws to assemble the device and separation with overlap all around the device where the top meets the bottom. This overlap causes poor weather sealing. Metal detector wands are usually comprised of a handle portion and a coil portion. In the prior art a copper magnet wire or ferrite coil assembly was inserted into the coil portion of the metal detector wand. All or some of the detector circuitry was generally placed in the handle portion of the wand.

In the prior art shielding to reject body capacitance and other noise interference would often be added in the form of shielding tape, paint or conduit, often with a grounding wire or tab.

### SUMMARY OF THE INVENTION

The present invention in one embodiment provides a metal detector comprising a coil, a circuit board on which the coil is etched, a digital signal processor, and a warning circuit. Embodiments with more than one coil are also contemplated. Shielding is also preferably etched onto the circuit board for grounding. Although a digital signal processor is preferred an analog processor can be employed. The term "digital signal processor" is used in a broad sense to mean any device capable of processing digital signals. The digital signal processor used preferably is a microcontroller.

When a sufficient amount of metal is near the coil the digital signal processor sends a signal to the warning circuit to activate one or more warning devices. The etched nature of the coil provides mechanical stability and reduces cost; the digital signal processor provides accurate detection which is not subject to drifting or as sensitive to temperature, humidity, body capacitance or other factors; and the warning circuit provides the user with an indication that a sufficient amount of metal is present.

Embodiments having separate receiver and transmitter coils are also contemplated. Multiple board layers of coils are also possible. Grounded shielding and circuitry can be provided on one or more layers. It may be preferable for some purposes to use multiple board layers of coils, such as when separate receiver and transmitter coils are used or when many oscillator coil winds are used.

The present invention in another embodiment provides a metal detector comprising an elongated coil and preferably grounded shielding etched onto an elongated circuit board. At least one active device, which is part of detection circuitry, is also preferably placed on the elongated circuit board. The detection circuitry in one embodiment, includes circuitry which along with the elongated coil forms an oscillator circuit. In other embodiments, separate receiver and transmitter coils could be employed on different board layers. The elongated circuit board is especially adaptable to slide or fit into a preferably elongated, molded, and unibody covering case or housing. The covering case or housing are preferably molded such as by blow molding or injection molding.

The elongated covering case typically includes a handle on one end for a user to hold onto. The covering case of the present invention is preferably not injection molded but of course the etched circuit coil or non-etched modular coil can also be fitted in such an injection molded covering case.

The covering case may actually be comprised of two pieces, one for the handle portion and one for the coil portion, which fit together and can be secured together. The present invention includes the method of using one molded piece, cutting that piece into two portions, such as a handle portion and a coil portion, inserting a circuit board, battery, or other components, and then joining the two portions of the covering case together. The two portions can be joined with two or more screws, a metal clamp, or in any other manner.

The above technique of cutting the one molded piece into two pieces allows a wide coil end, yielding better sensitivity, and the narrowest handle for better ergonomics. The circuit board can be glued to foam and pressfit into the case, or may be fixed by screws. A blowmolded, rotationally molded or extrusion molding of the covering case also produces a stronger, seamless, case, since unlike the prior art there is no overlap, but rather from top to bottom a unibody casing.

Preferably the covering case is made from high density plastic resin. Blowmolding is less expensive to make the mold, to mold each case, but permits less detailing. The mold will often last longer than prior art cases. This method can eliminate the need for a separate battery cover. Injection molded cases can also be engineered in a similar manner, at higher cost, to accommodate a coil on board.

The elongated and etched coil is particularly useful for security screening, such as in airports, prisons, and court-houses. The elongated shape allows the coil to quickly scan a person's body and the etched nature provides mechanical stability for the coil. Providing detection circuitry on the same circuit board makes it possible to manufacture a more

compact detection device, or to make the handle hollow and of narrower and more ergonomic cross section. It also greatly reduces noise or vibration in the sensitive connection between the coil and the detection circuitry. Providing the ability to slide or fit the board in and out of the elongated covering case allows the easy substitution of an old board for a new board, or a board having one type of coil and detection circuitry with, for a board having another type. In some embodiments of the invention, the etched coil is formed in fatter or rounder configurations for higher sensitivity for certain prison, theft, and law enforcement applications; for ground search of coins, precious metals, mines, shell casings, conduits, wiring and other metal items.

Shielding on a circuit board provides a less expensive, more compact and more uniform method and apparatus for shielding than prior art techniques.

### BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a view of a typical prior art plastic case;

FIGS. 2A–C are views of a covering case and printed circuit board on which a coil is etched;

FIG. 3 is a diagram of the top surface of the printed circuit board in FIG. 2A, showing an etched coil with some ground plain shielding;

FIG. 4 is a diagram of the bottom surface of the printed circuit board in FIG. 2A with ground plane shielding;

FIG. 5 is a diagram of the etched coil of FIG. 3 with detection circuitry shown on the inside of the coil;

FIG. 6 is a diagram of the etched coil of FIG. 3 with detection circuitry shown outside of the etched coil;

FIG. 7 is a block diagram of the detection circuitry and the etched coil;

FIG. 8 is a detailed schematic of detection circuitry and a coil in accordance with an embodiment of the present invention;

FIG. 9 is a diagram of a rounded etched coil in accordance with another embodiment of the present invention;

FIG. 10 is a diagram of a coil with an inner portion and an outer portion;

FIGS. 11A and 11B is a diagram of an alternative covering case;

FIGS. 12A–12C illustrate another embodiment for an apparatus and method for a covering case;

FIG. 13 illustrates a technique for mounting a circuit board to a covering case;

FIGS. 14A–D illustrate another embodiment of an apparatus and method for a covering case; and

FIGS. 15A–C illustrate another embodiment of an apparatus and method for a covering case.

### DETAILED DESCRIPTION OF THE DRAWINGS

FIG. 1 illustrates a prior art covering case 10 for a coil and electronic circuitry for a metal detector. The covering case 10 includes a top portion 12 and a bottom portion 14. The top portion 12 of the covering case 10 has an internal width  $T_i$  which is slightly smaller than its outer width  $T_o$ . The internal and outer width  $T_i$  and  $T_o$  respectively vary from a fixed smaller width in the handle portion 16 to a gradually increasing width in the transition portion 17, to a fixed larger width in the coil portion 18. The outer width  $B_o$  of the bottom portion 14 of the covering case 10 varies in width in a similar manner. The outer width  $B_o$ , of the bottom portion 14 is made smaller than the internal width  $T_i$ , of the top

portion 12, all along the covering case 10 so that the bottom portion 14 fits within the top portion 12. Thus the top portion 12 overlaps the bottom portion 14. The top portion 12 is then secured to the bottom portion 14 by screws (not shown) which are inserted through holes 20, 22, 24, 26, 28, and 30 and received by threaded receivers 40, 42, 44, 46, 48, and 50 respectively. A battery cover 15 is provided and is secured to the bottom and top portions 12 and 14 by screws being inserted through holes 70 and 72 and received by threaded receivers 60 and 62 respectively.

FIGS. 2A, 2B, and 2C illustrate cross sectional, top, and rear views, respectively, of a detector 110 in accordance with the present invention. The detector 110 is comprised of an elongated covering case 112, an elongated circuit board 118, and a battery 126. The circuit board 118 is preferably thin. The covering case 112 is typically comprised of two sections, a handle 114, and an elongated or body portion 116. The covering case 112 also includes an opening 120, shown in FIG. 2C, which is adapted for sliding or placing the circuit board 118 into the covering case 112. Alternatively a covering case may be provided which has a top and bottom half. However, it is preferred that the covering case 112 be constructed of a unibody structure or at least unibody in construction from top to bottom as will be shown in later embodiments. Unlike the prior art of FIG. 1, preferably the covering case 112 is not separated into top and bottom portions with many screws securing the portions together.

After the circuit board 118 is placed into the covering case 112, it can be fixedly mounted by screws, or snapped in place, press fit or glued with foam between the board and the case, or secured by any other means known in the art. The covering case 112 is preferably comprised of one or more parts, or molds. Preferably these one or more molds are not top and bottom portions but rather may preferably be comprised of portion such as the handle portion 114 and the elongated or body portion 116. This is more efficient than the prior art covering cases which typically required three or four molded parts, including top and bottom portions, as shown in FIG. 1, usually made using injection molding. Foam 128 is preferably placed between the battery 126 and the circuit board 118 as shown in FIG. 2C. A cover, not shown, may be placed so as to cover the battery 126, opening 120, and foam 128.

The length “LC” of the covering case 112 can be approximately sixteen inches but will vary depending upon the application. Sixteen inches is particularly suitable for security use. The width “WC” of the covering case is typically two to five inches. The covering case 112 may also be rounded or constructed in other shapes and forms, and may be mounted on an elongated pole for ground search. The cross section “HC” of the handle 114 is preferably narrow which is easier if no main circuit board is placed therein. The elongated circuit board 118 may preferably be placed in the elongated circuit portion 116. Handle free pocket models can be made and can be held with the coil end in the palm of the hand. A battery 126 may be placed in the handle 114 as shown in FIG. 2A or the battery 126 may be placed in a midsection between a coil on the elongated circuit board 118 and the handle 114, or between the elongated circuit board 118 which is shortened (not shown) and the handle 114.

FIGS. 3 and 4 illustrate the top surface 122 and the bottom surface 124, respectively, of the elongated circuit board 118. The elongated circuit board 118 has an elongated coil 200 comprised of six windings, etched on the top surface 122 as shown in FIG. 3. The six windings are preferably placed close together but do not touch each other. Although six windings are shown, any number of windings is contem-

plated by the present invention. For certain applications many or less windings may be preferred. For other applications many windings may be preferred. The elongated coil **200** can be connected to other circuit elements through its two terminals **202b** and **204a**. Terminal **202b** is connected to elongated coil **200** through conductor **202c** and terminal **202a** as shown in FIG. 4. Conductor **202c** is etched to the bottom surface **124** of the elongated circuit board **118**.

The elongated circuit board **118** also has etched on its top surface **122** a middle layer of shielding **210**, which comprises an inner shielding **212** and an outer shielding **214**. Alternatively, multiple layers can be provided. A bottom layer of shielding **216**, shown in FIG. 4, is etched to the bottom layer **124** of the elongated circuit board **118**. A top layer of shielding, not shown, may be painted on or omitted on top of the middle layer of shielding **210** and has a pattern which is the horizontal mirror image of the pattern for the bottom layer of shielding **216**, in FIG. 4, except the top layer preferably does not have conductor **202c**. The top layer of shielding may also be placed on a separate printed circuit board. The middle and bottom layers of shielding **210** and **216**, respectively, and the top layer of shielding, not shown, are connected at holes **220** by plated through conductors. The shielding **210** and **216** and the coil **200** are both preferably made of copper which has been etched onto the circuit board **118**. The shielding **210** and **216** may also be painted on.

A ground terminal **230** is shown connected to the outer shielding **214** of the middle layer of shielding **210** in FIG. 3. The ground terminal **230** is also shown connected to the bottom layer of shielding **216** in FIG. 4.

The coil **200** in one embodiment is 3.5 inches in width "W" and 10 inches in length "L" as shown in FIG. 3. The circuit board can be fiberglass or any other suitable material known in the art such as a plastic material.

Note that alternatives can be constructed such as multiple layer boards to accommodate extra receiver or transmitter windings or additional shielding.

FIGS. 5 and 6 show various ways in which detection circuitry can be placed in relationship to the elongated coil **200** of the present invention. In FIG. 5, detection circuitry **300** is shown placed inside the inner windings of the elongated coil **200**. This enables the production of a smaller detector **110**. FIG. 5 is merely an illustration and more space may be necessary for detection circuitry than shown by the dashed lines for detection circuitry **300**. The coil **200** in the FIG. 5 illustration may have to be larger to allow for extra circuitry, and an appropriate length of the coil is 9.5 inches. A terminal **204b** is provided for the FIG. 5 embodiment. The terminal **204b** is connected to the terminal **204a** through a conductor on the bottom surface **124** of the circuit board **118**, similar to the connection shown between terminals **202a** and **202b** in FIG. 3. Terminals **202a** and **204b** are shown connected by conductors **203a** and **203b** to the detection circuitry **300**. Other modifications for the FIG. 5 embodiment may be preferable for implementation, and these will be apparent to those skilled in the art.

FIG. 6 shows an elongated circuit board **218** which is longer than circuit board **118** in order to provide an area outside the coil **200** to place detection circuitry **300**. In the FIG. 6 embodiment terminals **202b** and **204a** are connected by conductors **205a** and **205b**, respectively, to detection circuitry **300**. In both FIGS. 5 and 6 the coil **200** and the detection circuitry **300** preferably lie in the same plane. Preferably the detection circuitry **300** is etched to either circuit board **118** or **218** and on the same side of the circuit

board as the etched coil **200**. The detection circuitry **300** typically includes one or more active components as will be described in more detail.

A block diagram of detection circuitry **300** electrically connected to elongated coil **200** is shown in FIG. 7. Detection circuitry **300** typically includes the circuit **400**, processor circuit **500**, and warning circuit **600**. Other types of circuits are also common which use separate receiver and field coil windings, which are physically positioned or tuned so as to null out crosstalk. The elongated coil **200** and the circuit **400** together comprise an oscillator **700**. The coil **200** alternatively may comprise separate receiver and transmitter windings. The receiver and transmitter windings may be wound opposite to each other and may be on separate boards or separate layers.

In operation, when metal is near the coil **200**, the frequency of the oscillator circuit **700** is changed. The frequency change is sensed by the processor circuit **500**. If the change exceeds a threshold, the processor circuit activates one or more warning devices in warning circuit **600**. Other types of circuitry known in the art can be used, such as circuits which use separate receiver and field coil windings, which are physically positioned or tuned so as to null out crosstalk. The detection and warning circuitry, whether of the oscillator type, the receiver/transmitter type, or otherwise are well known to those skilled in the art.

FIG. 8 is a more detailed schematic of detection circuitry **300** shown connected to the coil **200**. The coil **200** and circuit **400** comprise an oscillator circuit **700**. The oscillator circuit **700** shown in FIG. 8 includes a capacitor **402** connected in parallel with a resistor **404**, the two components connected at one end to a five volt supply and at the other end to the base of a transistor **406**. Capacitor **402** has a value of 0.005 microfarads and resistor **404** has a value of 220 kilo ohms. Transistor **406** is preferably a 2N2222A NPN bipolar transistor. The transistor **406** has a capacitor **408** having a value of 0.001 microfarads, connected across its emitter and collector terminals.

The transistor **406** provides amplification and functions as an active device in the oscillator circuit **700**. A capacitor **410**, having a value of 0.0068 microfarads, is connected at one end to the emitter of the transistor **406** and at the other end to a five volt supply. A resistor **412**, having a value of 1 kilo ohm, is connected at one end to the emitter of the transistor **406** and at the other end to ground. A resistor **414**, having a value of 100 kilo ohms, is shown connected at one end to node "A" and at the other end to ground. The oscillator circuit **700** is basically a Colpitts oscillator where capacitors **408** and **410** determine the frequency of oscillation. Resistors **404**, **412**, and **414** bias the transistor **406** and capacitor **402** filters out high frequency power supply noise.

The oscillator **700** is connected to processor circuit **500** at node A. The processor circuit includes digital signal processor **520**, mode circuits **530**, sensitivity circuit **550**, power on circuitry **560**, system clock **570**, and power circuit **580**.

The digital signal processor **520** receives the output of oscillator circuit **700**, from node "A" after that output has been properly modified by coupling capacitor **512**, and resistors **514**, **516**, and **518**. The coupling capacitor **512** eliminates low frequencies and the resistors **514**, **516**, and **518** set an appropriate D.C. level for the microcontroller or digital signal processor **520**. The capacitor **512** and the resistors, **514**, **516**, and **518** have values of 0.005 microfarads, 24 kilo ohms, 24 kilo ohms, and 4.7 kilo ohms respectively.

The digital signal processor **520** has four inputs connected to mode circuit **530**. Mode circuit **530** includes Multiple Dip

switch **532**, comprised of Dip switches **532a**, **532b**, **532c**, and **532d**, and jumper **540**. The input of Dip switches **532b**, **532c**, and **532d** are connected to one end of pullup resistors **534**, **536**, and **538** respectively, which are all connected at their other end to a five volt supply. The pullup resistors **534**, **536**, and **538** each may have a value of 100 kilo ohms. The outputs of Dip switches **532b**, **532c**, and **532d** are connected to ground. When these Dip switches are activated the microcontroller **520** sees a logic "0" at the respective input. When the Dip switch is not activated the microcontroller **520** sees a logic "1" at its input.

The Dip switches are used to set various modes of operation. The Dip switch **532a** changes between two volumes for an audio alarm **510**. Dip switch **532b** changes between high and low sensitivities for detection. Dip switches **532c** and **532d** are preferably adapted to change between different tones. One of these tones may be a Geiger counter tone where the time period between clicks increases with an increase in metal. A second of these tones may be a ramp tone where a steady tone is generated but the frequency of the tone increases with an increase in metal. The third of these tones may be a two tone where there is an alternation between two tones and the period between alternations increases with an increase in metal.

Jumper **540** is a hardware jumper. If the jumper **540** is connected between +5 volts and the middle pin, the detector **10** is a first model. If the jumper **540** is connected between ground and the middle pin the detector **110** is a second model of detector. In the first model, all dip switches are disabled, and the tone, sensitivity, and volume are at a default setting. In the second mode, the DIP switch is enabled.

Sensitivity circuit **550** includes a potentiometer **552** and a measuring resistor **554**. The potentiometer **552**, is a 100 kilo ohm potentiometer, which is connected to an input/output of the digital signal processor **520**, and the potentiometer **552** can be set by a user to achieve a level of sensitivity for detection of metal. The measuring resistor **554** having a value of 68 kilo ohms, is used to provide a reference resistance. A resistor **556**, having a value of 100 kilo ohms, is shown connected to the 9 volt supply and is used for battery detection. A capacitor **558**, having a value of 33 nanofarads first discharged by the microcontroller. The microcontroller then charges capacitor **558** through resistor **554** and measures the time for the voltage across the capacitor **558** to pass a threshold, to be used as a reference. The digital signal processor **520** then repeats the process but adds potentiometer **552**, measures the charge time, and determines the resistance by the difference in the rise times. The same process is used to measure battery voltage using resistor **556**.

The power on circuitry **560** includes resistor **562** and **564**, which have values of 100 kilo ohms and 10 kilo ohms respectively. One end of resistor **562** is connected to the reset terminal of digital signal processor **520** and the other end is connected to the 9 volt supply. Resistor **564** has one end connected to ground and the other to the 9 volt supply.

The system clock **570** preferably comprises a crystal or a ceramic resonator, which along with the internal oscillator circuit of the digital signal processor **520** preferably generate the clock for the digital signal processor **520**.

Power circuit **580** includes a 9-volt battery **582** connected at its output to a first pole of a momentary switch **584**. The switch **584** can be replaced by an on/off switch. The second pole of the momentary switch **584** is connected to one end of a capacitor **586**, whose other end is connected to ground.

The capacitor **586** has a value of 100 nanofarads. The second pole of the momentary switch **584** is also connected to an input of a voltage regulator **588**. The output of the voltage regulator **588** is connected to one end of a capacitor **590**, whose other end is connected to ground. Capacitor **590** has a value of 6.8 microfarads. A Capacitor **592** is connected at one end to ground and at its other end to the five volt supply and to an input of the digital signal processor **520**. The capacitor **592** has a value of 0.1 microfarads and is used for basic power supply bypassing for the digital signal processor **520** as known in the art.

After the momentary switch **584** is closed a nine volt supply is provided at node "B" and a 5 volt supply is provided at node "C". The capacitors **586** and **588** are needed by the voltage regulator for stability and to improve transient response. The nine volt and five volt supplies are provided to other parts of the detection circuitry **300** and coil **200** as shown.

Warning circuit **600** comprises audio alarm **610** and LED alarm **640**. Audio alarm **610** includes resistor **620**, having a value of 2.8 kilo ohms, whose one end is connected to an output of digital signal processor **520** and whose other end is connected to the bases of transistors **622** and **624**. The emitter of transistor **622** and the collector of transistor **624** are connected together at node D. The collector of transistor **622** is connected to the nine volt supply. The emitter of transistor **624** is connected to ground. Node D is connected to one end of a capacitor **626**, having a value of 22 micro farads. The capacitor **626** filters low frequencies. The other end of the capacitor **626** is connected to the high input of speakers **630**, **632**, and **634**. The low inputs of the those speakers are connected to one end of resistor **636**, which has a value of 68 ohms, at node "E". The other end of resistor **636** is connected to ground. Node "E" is also connected to the output of Dip switch **632a**. The input of Dip switch **632a** is connected to ground.

LED alarm **640** includes a resistor **642** which is connected at one end to an output of the digital signal processor **620** and at its other end to an input of LED **644**. The output of LED **644** is connected to an output of digital signal processor **520**. The input of LED **644** is also connected to a resistor **646**, which is connected at its other end to the five volt supply.

Both one color and two color LEDs **644** can be used for visual alarm. If a single color LED **644** is used, a 1 kilo-ohm resistor **646** is used and the digital signal processor **520** will pulse width modulate the LED **644** to increase the intensity with an increase in the presence of metal. If a two color LED **644** is used, a 150 ohm resistor **642** is used and the digital signal processor **520** will pulse width modulate the LED **644** with alternating polarity to go from green to yellow to red with an increase in the presence of metal. The LED **644** can be provided to become brighter when more metal is present.

In operation, oscillations are continuously produced at Node "A" by the oscillator circuit **700**. The oscillations are counted by the digital signal processor **520** and a "no metal present" count is determined. When metal is placed near the coil **200** of the oscillator circuit **700**, the frequency of oscillation changes. The oscillations are counted and a "metal present" count is determined. If the difference between the two counts exceeds a threshold, the LED alarm **640** and the audio alarm **610** of the warning circuit **600** are activated to indicate that metal has been detected. The LED alarm **640** preferably gets brighter as increasing amounts of metal are detected. The sound of the audio alarm **610** preferably also increases as more metal is detected.

The digital signal processor **520** is preferably a microcontroller, and may be a P1C16C54 microcontroller. Pins **p6** through **p13** of the digital signal processor **520** comprise an 8-bit bus. Pins **p17**, **p18**, **p1**, and **p2** comprise a 4-bit bus. Pin **p3** is an input to a real time counter. Pins **p16** and **p15** are clock inputs for system clock **470**. Pins **p14** and **p5** are voltage supply inputs and **p4** is reset input.

The digital signal processor **520** preferably includes a counter which has a pre-scaler. The pre-scaler allows higher frequencies to be measured with slower and cheaper digital signal processors **520** by dividing down the oscillator frequency so that a slower and cheaper digital signal processor **520** can count the frequency of oscillation. Accurate frequency measurement can be achieved by gating the input to the counter. By using a tri-statable I/O pin on the digital signal processor **520**, frequency measurement can be achieved as follows: 1. Output a **1** to pin **p2** of digital signal processor **520**, which is received by pin **p3**, and this input disables the counter in the digital signal processor **520**, while still allowing the oscillator **700** to oscillate due to resistor **514** and capacitor **512**. 2. Reset the counter in the digital signal processor **520**. 3. Place **p2** of digital signal processor **520** in a high impedance state for an exact period of time to allow the oscillator signal to increment the counter. 4. Output a **1** to **p2** of the digital signal processor **520**. 5. Read the counter in the digital signal processor **520**. 6. Alternate **O, 1**, to the I/O pin **p2** of the digital signal processor, while reading the counter to determine the count in the prescaler. Add the prescaler count to the original count to get the frequency.

A preferred frequency of operation of the oscillator circuit **700**, without metal present, is approximately 2 megahertz.

FIG. 9 illustrates a rounded etched coil **800** etched on a circuit board **818** in accordance with the present invention. The circuit board **818** has terminals **802a**, **802b**, **830**, and **804a** which are analogous to the terminals **202a**, **202b**, **230**, and **204a** of FIG. 3. The circuit board **818** includes detection circuitry **810** which is connected to the coil **800**. Conductors **803a** and **803b** connect the terminals **802b** and terminal **804a** of the coil **800**, with the detection circuitry **810**. The detection circuitry **810** may be the same as the detection circuitry **300** illustrated in FIG. 8. The dimensions of the circuit board **818** are not to scale and may vary depending upon the application.

Although the detection circuitry, such as detection circuitry **300** of FIG. 8, and coil **200** were discussed by using specific component values, it will be apparent to those skilled in the art that the present invention can be implemented in various forms using various components. In the present application the term "connected" is used in a broad sense and includes operable "connections" between wireless terminals and devices.

Although a rectangular elongated coil **200** has been disclosed in one embodiment, an elongated coil comprised of various coil configurations, including essentially round coil windings for greater sensitivity constructed on a relatively elongated circuit board is contemplated by the present invention. Each coil configuration may have differing sensitivities and other characteristics which can be switched to depending on the application.

FIG. 10 shows a board **910** and an etched coil **920** in accordance with another embodiment of the present invention. The etched coil **920** has separately inter-spaced co-planar outer winds **922** and inner winds **924**. The outer winds **922** are comprised of three winds and the inner winds **924** are comprised of two winds. Various other configurations can be provided. The etched coil **920** can be used with the other components and electronic circuitry shown for FIGS. 1-9. The coil **920** may be not etched, but rather wound as in the prior art. However the etched coil **920** is

capable of greater uniformity of detection for both a range of large and small metal objects.

Inter dispersed coil windings such as shown in the embodiment of FIG. 10, are especially inexpensive to effect by etching on a board, where they are easily located and fixed consistently without resorting to glue or epoxy. Nevertheless this more uniform field winding may be included when the coil such as coil **920** is wound discretely. Discrete coil windings embedded in foam or substrate to form a module, when inserted into a one piece coil end of a plastic case, such as a blow molded, roto-molded or extruded case. Such as case is included in connection with coil windings on a circuit board, however the case can be cut for battery access or to allow board insertion, or where the case becomes attached in manufacture to a section which is injection molded or thermoformed. The later cases are intended to be covered where they house board etched metal detector coil windings. The above metal detector windings etched on a circuit board can also be used in another preferred embodiment to replace discrete windings, with or without board shielding, for the sides of a walkthrough security detector or a quality control when positioned on either side of a conveyORIZED processing line. In this case the side housing can be a wound plastic metal or other similar material.

The width  $W_2$  and the length  $L_2$  of the coil **910** may be three inches and eight inches, respectively. The inner winds **924** are provided so that there is no dead zone in the center of the coil for small objects. Electronic components can be provided in between the outer winds **922** and the inner winds **924**.

FIGS. 11A and 11B are cross sectional and perspective views of a metal detector wand **1010** in accordance with another embodiment of the present invention. Metal detector wand **1010** include covering case **1012**, circuit board **1014**, battery-board interface **1016** and battery **1018**. The circuitry of the metal detector wand **1010** may be as previously described with reference to FIGS. 1-10. The battery **1018** protrudes out from the covering case **1012** allowing for the easy insertion or removal of the battery **1018**. The covering case **1012** is preferably of unibody construction and can be blow molded, rotomolded, or molded in any other manner. The covering case **1012** as shown in FIG. 11B resembles a hollow closed rectangular box with one open end **1022**. The unibody molding of the covering case **1012** in accordance with the present invention provides a stronger and more lasting structure than for example the prior art embodiment of FIG. 1.

The perspective view of FIG. 11B shows the insertion of foam **1020** between the walls of the covering case **1012** and the area for the battery **1018**. The circuit board **1014** can be mounted to the bottom of the covering case **1012** by gluing or in any other manner.

FIGS. 12A, 12B, and 12C illustrate a method and apparatus for forming a metal detector wand **1110** in accordance with the present invention. FIG. 12A shows a molded unibody structure **1105**. This structure is a unibody in the sense that it is molded entirely in one piece, with the exception of a hole **1109**. In accordance with a method of the present invention the molded unibody structure **1105** is cut along lines **1106** and **1108** to remove the center portion **1107**. With the center portion **1107** removed the molded unibody structure is now separated into a handle portion **1116** and a coil portion **1114**. The inner dimension,  $C_r$ , of the coil portion **1114** and the first outer dimension  $B_r$ , of the handle portion **1116** are preferably such that the handle portion **1116** fits inside the coil portion **1114**. As shown in FIG. 12B preferably a battery **1130** is placed in the handle portion **1116** and a circuit board **1120** is placed in the coil portion **1114**. Wires **1132** are used to connect the battery **1130** with the

## 11

circuit board **1120**. The circuit board **1120** may be mounted in any manner known in the art. FIG. **12C** shows the handle portion **1116** and the coil portion **1114** connected together. In the embodiment of FIG. **12A–C**, ridges **1150** are used to snap the two portions together. The two portions could also in some embodiments be screwed together. The joining area where the handle portion **1116** and the coil portion **1114** are joined together is much shorter than the joining area of the prior art such as shown in FIG. **1**. The joining area of the handle portion **1116** and the coil portion **1114** is preferably orthogonal to the joining area of prior art devices such as shown in FIG. **1**.

FIG. **13** illustrates a technique for mounting a circuit board **1220** to a covering case **1212**. This technique can be used in conjunction with any of the previous embodiments. Screws **1240** and **1242** can be inserted through standoffs **1230** and **1232** and securely fashioned. The standoffs **1230** and **1232** are preferably glued to the circuit board **1220** or attached in another manner.

FIGS. **14A–D** illustrate a method and apparatus for making a metal detector wand covering case **1312**. FIG. **14A** shows a unibody molded structure **1305**. To create the covering case **1312**, the unibody molded structure **1305** is cut along the lines **1306** and **1308**, and the section **1307** is removed. A circuit board **1319** with preferably etched coil and electronics and an attached battery **1320** are inserted into a hollow coil portion **1316** as shown in FIG. **14B**. A handle portion **1314** is then inserted into the coil portion **1316**. As shown in FIG. **14B** a section **1318** of overlap of the handle portion **1314** and coil portion **1316** occurs. The handle portion **1314** and coil portion **1316** are preferably glued, bolted, or screwed together at the overlap section **1318**. A completed covering case **1312** comprising a unified handle portion **1314** and a coil portion **1316** is shown by FIG. **14C** and **14D**. FIG. **14C** shows a top view and FIG. **14D** shows a perspective view.

FIGS. **15A–C** illustrates an apparatus and method for creating a covering case **1412**. In this example a handle portion **1414** has three sections one of a thinner width **1414a**, one portion of an increasing width **1414b**, and one portion of a larger width **1414c**. The handle portion **1414** is again inserted into the coil portion **1416**. As shown in FIG. **15C**, an opening **1450** is provided in the coil portion **1416**, into which the handle portion **1414** is inserted. After the handle portion **1414** has been inserted into the coil portion **1416**, the two portions can be secured in any manner, such as by screws **1420** and **1422** through holes **1430** and **1440**, and screws **1424** and **1426** through holes **1442** and **1432**, as shown in FIG. **15C**, assumin the handle portion **1414** has been inserted into the coil portion **1416**. In this embodiment the smaller width **1414a** of the handle **1414** may be desirable for ease of manipulating a metal detector and for a lighter weight metal detector. Metal clamps may be used to sandwich the handle portion **1414** and the coil portion **1416** together.

We claim:

1. A method of making a metal detector comprising:
  - etching a coil onto a circuit board;
  - mounting detection circuitry on the circuit board;
  - and providing a housing surrounding the coil and the detection circuitry.
2. The method of claim 1 further comprising the step of:
  - etching shielding on the circuit board to shield body capacitance or RF noise.
3. The method of claim 1 wherein:
  - the detection circuitry mounted on the circuit board is connected to a power source.

## 12

4. The method of claim 1 further comprising the step of:
 

- applying shielding on the circuit board by painting.

5. The method of claim 1 further comprising the step of:
 

- applying shielding on the circuit board by tape.

6. The method of claim 1 wherein:

the step of providing the housing includes providing a body portion and a handle wherein:

- the body portion surrounds the circuit board; and
- the handle is provided with a smaller cross section than the body portion.

7. The method of claim 6 wherein:

the handle does not directly surround the circuit board.

8. A method of making a metal detector comprising:

- etching a coil onto a first circuit board;
- mounting detection circuitry onto a second circuit board;
- and providing a housing surrounding the coil and the detection circuitry.

9. The method of claim 6 further comprising the steps of:
 

- molding the body portion of the housing in one piece;
- and inserting the circuit board into the body portion of the housing.

10. The method of claim 9 further comprising:

fixing the circuit board to the body portion of the housing.

11. The method of claim 1 wherein

the housing is comprised of a body portion and a handle, the body portion and the handle being one and the same and the body portion and handle surrounding the coil.

12. The method of claim 1 further comprising:

providing digital detection circuitry.

13. The method of claim 6 further comprising:

providing a power source;

and providing an opening in the housing for both the insertion of the power source and the insertion of the circuit board.

14. The method of claim 1 further comprising:

providing the housing in at least two sections, a handle section and a body portion section.

15. The method of claim 1 further comprising:

making the housing by blowmolding.

16. The method of claim 1 further comprising:

making the housing by injection molding.

17. The method of claim 1 further comprising:

making the housing by extruding.

18. The method of claim 14 further comprising:

cutting a unibody mold into at least two pieces;

and reassembling the two pieces.

19. A metal detector apparatus comprising:

a coil;

a circuit board;

detection circuitry mounted to the circuit board;

wherein the detection circuitry is comprised of:

- a warning circuit,
- a power source,
- a housing surrounding and protecting the coil,
- and the circuit board, the housing comprising a handle;

wherein the coil is comprised of windings which are supported in at least one plane by the circuit board so that the windings are spread out substantially uniformly from the center of the circuit board to the periphery of the circuit board.